

MICHI

X5

STEREO INTEGRATED AMPLIFIER



2 x 600 Watts of robust power



Class AB amplifier design



AKM premium 32-bit/768kHz Digital to Analog Converter



Bluetooth with apt-X and AAC



Balanced XLR inputs



Includes remote control

The Michi X5 Integrated Amplifier is Performance Redefined delivering an astounding 600 Watts of Class AB power into 4 ohm speakers even under the most extreme loading conditions. The X5 is replete with inputs ensuring support of all popular audio sources including analog, digital, XLR, PC-USB, apt-X Bluetooth, and selectable Moving Magnet or Moving Coil Phono stage.

The acoustic eminence of the X5 is achieved utilizing a perfect balance of innovation and critical engineering of every circuit, signal path and audio component ensuring the exquisite industrial design is surpassed only by breathtaking performance.

Musical expression of the X5 is evidenced by the exceptional control of near limitless bass energy and essential clarity of the midrange and high frequencies. The X5 delivers true-to-life audio reproduction ensuring meticulous accuracy of the musical timing with exacting spatial positioning be it a solo artist or full orchestral symphony.

The X5 oversized, in-house manufactured toroidal transformer feeds 88,000uF of high efficiency bulk storage smoothing capacitors with isolated power supply feeds to all acoustically sensitive circuits eliminating unwanted noise or distortion further refining the audio.

A front panel high-resolution graphic display is configurable to show operating status, 12 band Graphic EQ or Peak Power Meter. Front panel control knobs and included Michi remote control assure easy operation and configuration.

Dual sets of Rhodium plated custom Michi speaker binding posts allow effortless connection to loudspeakers including bi-wire installations. RS232 and Ethernet connections allow simple integration with control systems.

Welcome to Michi. Acoustic Elevation, Sonic Evolution, Visual Perfection.

MICHI

X5

STEREO INTEGRATED AMPLIFIER



SPECIFICATIONS

Maximum Power Output	600 watts/channel (4 ohms)	Digital Section	
Continuous Power Output	350 watts/channel (8 ohms)	Frequency Response	20 Hz - 20k Hz (0 ± 0.4 dB)
Total Harmonic Distortion	< 0.009%	Signal to Noise Ratio (IHF "A" weighted)	102 dB
Intermodulation Distortion (60 Hz : 7 kHz, 4:1)	< 0.03%	Input Sensitivity/Impedance	0 dBFs / 75 ohms
Frequency Response		Preamplifier Output Level	1.2 V (at -20 dB Volume Position)
Phono Input	20 Hz-20k Hz (+1.5 dB, -0.2 dB)	Coaxial/Optical Digital Signals	SPDIF LPCM (up to 192kHz 24 bit)
Line Level Inputs	10 Hz-100k Hz (+0 dB, -1 dB)	PC-USB	USB Audio Class 1.0 (up to 96kHz 24-bit) USB Audio Class 2.0 (up to 384kHz 32-bit)* *Driver installation required DSD and DoP support
Damping Factor (20 Hz - 20kHz, 8 ohms)	350	Power Requirements	
Input Sensitivity / Impedance		Europe	230 V, 50 Hz
Phono Input (MM)	5.7 mV / 47k ohms	USA	120 V, 60 Hz
Phono Input (MC)	330 uV / 47k ohms	Power Consumption	850 watts
Line Level Inputs (RCA)	380 mV / 47k ohms	Standby Power Consumption	
Line Level Inputs (XLR)	580 mV / 100k ohms	Normal	< 0.5 watts
Input Overload		Network Wakeup	< 2 watts
Phono Input (MM)	199 mV	BTU (4 ohms, 1/8 power)	1239 BTU/h
Phono Input (MC)	22 mV	Dimensions (W x H x D)	485 x 195 x 452 mm 19" x 7 5/8" x 17 3/4"
Line Level Inputs (RCA)	12.5 V	Front Panel Height	132 mm / 5 1/4"
Line Level Inputs (XLR)	12.5 V	Weight (net)	42 kg, 92.59 lb
Preamplifier Output Level / Impedance	2 V / 100 ohms	Finish	Black
Tone Controls			
Bass	±10 dB at 100 Hz		
Treble	±10 dB at 10k Hz		
Signal to Noise Ratio (IHF "A" weighted)			
Phono Input (MM/MC)	80 dB		
Line Level Inputs	102 dB		
Channel Separation			
Phono Input (MM)	> 65 dB		
Line Level Inputs	> 65 dB		

All specifications are accurate at the time of printing.
Michi reserves the right to make improvements without notice.